

## WMS 80mm MAF TRANSFER FUNCTION

STOCK		MAF	MEASURED VALUES CLOSED LOOP							
VOLTS	#/M		VOLTS	#/M	COUNTS	LOAD	STFT-B1	SPEED	IAT	RPM
5	39.80863		5							
4.696	33.26834		4.696							
4.381	27.4365		4.381							
4.15	23.50751		4.15							
3.884	19.5399		3.884							
3.738	17.59606		3.738							
3.58	15.67216		3.58							
3.406	13.67904		3.406							
3.214	11.679		3.214							
3.089	10.48026		3.089							
2.997	9.663434		2.997							
2.807	8.189966		2.807							
2.582	6.676868		2.582							
2.455	5.898613		2.455							
2.316	5.109509		2.316							
2.163	4.327873		2.163							
1.992	3.58378		1.992							
1.892	3.198032		1.892							
1.66	2.441539		1.66							
1.523	2.03994		1.523							
1.45	1.837296		1.45							
1.286	1.428746		1.286							
1.195	1.237922		1.195							
1.088	1.040515		1.088							
0.964	0.847299		0.964							
0.814	0.641143		0.814							
0.743	0.563013		0.743							
0.608	0.435725		0.608							
0.528	0.3677		0.528							
0.032755	0		0.032755							